

1a 30A polarized power relays

FEATURES

- 1. 30A capacity in small size
- 2. Contributes to device energy
- savings with latching type. 3. High insulation
- 4,000V AC (between contacts and coil) Surge 10,000V (between contacts and coil)

Creepage distance and clearances between contact and coil: 8 mm

- 4. Sealed construction
- 5. UL/C-UL approved

DQ RELAYS (ADQ)

TYPICAL APPLICATIONS

- 1. Time switches
- 2. Electric water heaters
- 3. Remote control of electric power meters

ORDERING INFORMATION



TYPES

Contact arrangement	Nominal coil voltage	Part No.				
		1 coil latching	2 coil latching			
1 Form A	4.5V DC	ADQ13Q04H	ADQ23Q04H			
	6V DC	ADQ13Q006	ADQ23Q006			
	9V DC	ADQ13Q009	ADQ23Q009			
	12V DC	ADQ13Q012	ADQ23Q012			
	24V DC	ADQ13Q024	ADQ23Q024			

Standard packing: Carton: 20 pcs.; Case: 200 pcs.

RATING

1. Coil data

1) 1 coil latching

Nominal coil voltage	Set voltage* (at 20°C 68°F)	Reset voltage* (at 20°C 68°F)	Nominal operating current [±10%] (at 20°C 68°F)	Coil resistance [±10%] (at 20°C 68°F)	Nominal operating power	Max. applied voltage (at 20°C 68°F)
4.5V DC	70%V or less of nominal voltage	70%V or less of nominal voltage (Initial)	111.1mA	40.5Ω		130%V of nominal voltage
6V DC			83.3mA	72Ω		
9V DC			55.6mA	162Ω	500mW	
12V DC	(Initial)		41.7mA	288Ω		
24V DC			20.8mA	1,152Ω		

* Pulse, direction of measurement: Terminal is downward.

1



Panasonic ideas for life

DQ (ADQ)

2) 2 coil latching

Nominal coil voltage	Set voltage* (at 20°C 68°F)	Reset voltage* (at 20°C 68°F)	Nominal operating current [±10%] (at 20°C 68°F)		Coil resistance [±10%] (at 20°C 68°F)		Nominal operating power		Max. applied voltage (at 20°C 68°F)
-			Set coil	Reset coil	Set coil	Reset coil	Set coil	Reset coil	
4.5V DC	70%V or less of nominal voltage (Initial)	70%V or less of nominal voltage (Initial) (Initial)	221.7mA	221.7mA	20.3Ω	20.3Ω	1,000mW	1,000mW	130%V of nominal voltage
6V DC			166.7mA	166.7mA	36 Ω	36Ω			
9V DC			111.1mA	111.1mA	81Ω	81Ω			
12V DC			83.3mA	83.3mA	144Ω	144Ω			
24V DC			41.7mA	41.7mA	576Ω	576Ω			

* Pulse, direction of measurement: Terminal is downward.

S						
s Item		Specifications				
Arrangement		1 Form A				
Contact resistance (I	nitial)	Max. 30 mΩ (By voltage drop 6 V DC 1A)				
Contact material		AgSnO ₂ type				
Nominal switching ca	apacity (resistive load)	30 A 250V AC				
Max. switching powe	r (resistive load)	7,500 V A				
Max. switching voltage	je	250V AC				
Max. switching curre	nt	30 A				
Nominal operating po	ower	500mW (1 coil latching), 1,000mW (2 coil latching)				
Min. switching capac	ity (Reference value)*1	100mA 5 V DC				
Insulation resistance	(Initial)	Min. 1,000M Ω (at 500V DC) Measurement at same location as "Breakdown voltage" section				
Breakdown voltage (Initial)	Between open contacts	1,500 Vrms for 1min. (Detection current: 10mA.)				
	Between contact and coil	4,000 Vrms for 1min. (Detection current: 10mA.)				
Surge breakdown voltage*2 (Initial)	Between contact and coil	Min. 10,000 V				
Temperature rise (at 65°C 149°F) (coil)		Max. 50°C (By resistive method, max. switching current) (Coil; de-energized)				
Set time (at 20°C 68	°F)	Max. 20 ms (Nominal coil voltage applied to the coil, excluding contact bounce time.)				
Reset time (at 20°C	68°F)	Max. 20 ms (Nominal coil voltage applied to the coil, excluding contact bounce time.)				
Shock registered	Functional	Min. 200 m/s ² (Half-wave pulse of sine wave: 11 ms; detection time: 10µs.)				
SHOCK resistance	Destructive	Min. 1,000 m/s ² (Half-wave pulse of sine wave: 6 ms.)				
Vibratian registeres	Functional	10 to 55 Hz at double amplitude of 1.5 mm (Detection time: $10\mu s$.)				
VIDIALION TESISLATICE	Destructive	10 to 55 Hz at double amplitude of 2 mm				
Mechanical		Min. 10 ⁶ (at 180 times/min.)				
Electrical		Min. 104 (At nominal switching capacity, operating frequency: 3s ON, 3s OFF)				
Conditions for operate	ion, transport and storage*3	Ambient temperature: -40°C to +65°C -40°F to +149°F Humidity: 5 to 85% R.H. (Not freezing and condensing at low temperature)				
Max. operating spee	d	10 times/min. (at rated load)				
		Approx. 35 g 1.23 oz				
	S Arrangement Contact resistance (I Contact material Nominal switching cae Max. switching voltag Max. switching capac Insulation resistance Breakdown voltage (Initial) Surge breakdown voltage*2 (Initial) Temperature rise (at Set time (at 20°C 68 Reset 68 Reset time (at 20°C	Item Arrangement Contact resistance (Initial) Contact material Nominal switching capacity (resistive load) Max. switching power (resistive load) Max. switching current Nominal operating power Min. switching capacity (Reference value)*1 Insulation resistance (Initial) Breakdown voltage Inituation resistance (Initial) Breakdown voltage*2 (Initial) Between open contacts (Initial) Between contact and coil Surge breakdown voltage*2 (Initial) Between contact and coil Temperature rise (at 65°C 149°F) (coil) Set time (at 20°C 68°F) Reset time (at 20°C 68°F) Shock resistance Functional Destructive Vibration resistance Functional Destructive Mechanical Electrical Conditions for operation, transport and storage*3 Max. operating speed Intangent and storage*3				

Notes:

*1. This value can change due to the switching frequency, environmental conditions, and desired reliability level, therefore it is recommended to check this with the actual load.

*2. Wave is standard shock voltage of $\pm 1.2 \times 50 \mu s$ according to JEC-212-1981

*3. The upper limit of the ambient temperature is the maximum temperature that can satisfy the coil temperature rise value. Refer to "6. Usage, Storage and Transport Conditions" in AMBIENT ENVIRONMENT section in Relay Technical Information.

DQ (ADQ)

DIMENSIONS (mm inch)

Download CAD Data from our Web site.

CAD Data







2ç

SAFETY STANDARDS

UL/C-UL (Recognized)				
File No.	Contact rating			
E43149	30A 277V AC			

E43149 30A 277V AC * CSA standard: Certified by C-UL

NOTES

1. Coil connection

When connecting coils, refer to the wiring diagram to prevent mis-operation or malfunction.

2. Others

If more than 20 A is delivered via the plug-in terminal connection, to prevent loosening of contacts loss long periods of operation, ensure that the plug-in terminal is soldered to the receptacle terminal.

For Cautions for Use, see Relay Technical Information.